

EAP350

Long Range Ceiling Mount Access Point

- 2.4 GHz
- 300Mbps
- 11b/g/n
- 28dBm
- AP/WDS

PRODUCT OVERVIEW



EAP350 is a 300Mbps wireless-n ceiling mount AP which offers users extended coverage, strong penetration, secure network management and simple connection.

It provides extended coverage and at least 3 floors penetration in your environment. MSSID + VLAN make your data more secure and easy management. Standard PoE interoperable with 802.3af makes internet connection more flexible.

EAP350 designed as a Ceiling mount AP which will not violate your interior decoration. Only 3-step makes setting AP up simpler. EAP350 is the perfect choice for home and small business.

| SOFTWARE FEATURES | | |
|---------------------------------|------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|
| SYSTEM REQUIREMENTS | | |
| System | Windows Windows7, 98, ME, NT, XP, 2000. Mac OS X (10.4) | |
| Access method | Web Based (HTTP 1.0 / 1.1) | |
| Browser Compatibility | Microsoft IE 6.0 or above, Firefox 2.0 or above | |
| STATUS | | |
| System Status | System Information | System Up Time, Device Name, Wireless MAC, LAN MAC, Country, Current Time, Firmware Version |
| | Current IP Setting | IP Address, Subnet Mask, Default Gateway, DHCP, DNS. |
| | Current Wireless Setting | Operation mode, Wireless Mode, Channel/Frequency, L2 Isolation, MSSID Setting |
| Client List | List current associated clients. Show only authorized and associated clients | |
| System Log | Displays a list of events triggered | |
| WIRELESS FUNCTIONAL LIST | | |
| Operation mode | AP | |
| | WDS | |
| WDS details | WDS AP algorithm | |
| | WDS bridge algorithm | |
| 802.11 mode options | b/g/n | |
| Channel setting | Manual | |
| | Auto / Best Channel Selection | |
| Transfer rate setting | Auto and Manual | |
| Output Power Control | Select Box (100%, 75%, 50%, 25%, 10%) | |
| Power Saving | Wireless LAN power saving | |
| Multiple BSSID (Multi AP) | 4 BSSID for 2.4Ghz | |
| | Each BSSID should has its own WiFi & security settings | |
| WPS | Software only | |
| Security | WEP | WEP(64/128bit) |
| | WPA/ WPA2 | TKIP / AES |

| | | |
|-------------------------|-----------------------|------------------------------------------------------------------------------------------------------------------------------------------|
| | Hidden ESSID | |
| | MAC address filtering | MAC address filtering (WLAN, up to 32 field) |
| | L2 Isolation | |
| | 802.1x Authenticator | MD5/ TLS/ TTLS, PEAP (Nice to Have) |
| | 802.1x Supplicant | TTLS, PEAP (Nice to have) |
| LAN Settings | | IP (check validity and DHCP server IP range) MAC |
| DHCP server | | DHCP Range, Lease Time, Client list |
| VLAN | MSSID | VLAN tag on MSSID |
| | Management VLAN | Only allow user with specified VID to access the device |
| | Ethernet Port VID | |
| | Tag/ Untag Option | Independent VLAN setting can be enable or disable |
| | Add VLAN tag | Any packet that enters the Device without a VLAN tag will have a VLAN tag inserted with a PVID (Ethernet Port VID) |
| SNMP | SNMP V1/V2C | - SNMP Active : Disabled / Enabled |
| | MIBI, MIBII | - SNMP Version : V1/V2c/ALL |
| | Private MIB | - Read Community - Set Community - System Location - System Contract - Trap Active : Disabled / Enabled - Trap Manager IP |
| Administration | | User Name (set as "admin") |
| | | Password (can be changed by user) |
| | | Confirmed Password |
| Backup/ Restore Setting | | Save Current Setting Restore Saved Setting Reset to Factory Default |
| Firmware Upgrade | | Firmware Upgrade Allow User to decide to Keep current setting or reset to default. |
| Diagnosis | | Address to Ping : |

| TECHNICAL SPECIFICATIONS | | | |
|-------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------|-------------------------------------------------------------------------------------------------------------|
| HARDWARE SPECIFICATIONS | | | |
| MCU | AR7242+AR9283 | | |
| Memory | 32MB | | |
| Flash | 4MB | | |
| Diameter * Height | 120mm x 50mm | | |
| Physical Interface | LAN: 1 x 10/100/1000 Gigabit Ethernet RJ-45 (802.3af PoE standard supported) | | |
| | Reset button | | |
| | Power Jack | | |
| LED Definition | Power x1 | Green | Booting: Blink at 1H Booting System Ready: On Firmware Upgrade: Blink at 4Hz System Off: Power Off |
| | WLAN x1 | Green | Link: Solid Light / Active: Blinking (Receiving/ Transmitting data) |
| | LAN x1 | Green | Link: Solid Light / Active: Blinking (Receiving/ Transmitting data) |
| Adapter | 12V / 1A | | |
| WIRELESS SPECIFICATIONS | | | |
| Frequency Band | 2.400~2.484 GHz(11b, 11g, 11n) | | |
| Modulation Technology | OFDM: BPSK, QPSK, 16-QAM, 64-QAM DBPSK, DQPSK, CCK | | |
| Operating Channels | 11 for North America, 14 for Japan, 13 for Europe | | |
| Wireless Setting | Operation Mode – AP / WDS Wireless Mode – 11b/ 11g /11n Channel Selection (Setting varies by Country) Channel Bandwidth (Auto, 20Mhz, 40Mhz) Transmission Rate - 11n only , 11b/g/n mix , 11b only , 11b/g | | |
| Receive Sensitivity (Typical) | 2.412 ~ 2.472 GHz (11b) best ↳ -90 dBm 2.412 ~ 2.472 GHz (11g) best ↳ -88 dBm 2.412 ~ 2.472 GHz (11n) best ↳ -85 dBm | | |
| Available transmit power | 11b | 1Mbps - 11Mbps | 29 |

| | | | |
|---------|-----------------------|-----------------|----|
| | 11g | 6Mbps - 9Mbps | 29 |
| | | 12Mbps - 18Mbps | 28 |
| | | 24Mbps - 36Mbps | 24 |
| | | 48Mbps - 54Mbps | 23 |
| | 11n | MCS 0-1 / 8-9 | 26 |
| | | MCS 2-3 / 10-11 | 25 |
| | | MCS 4-5 / 12-13 | 24 |
| | | MCS 6-7 / 14-15 | 23 |
| Antenna | Internal 5dBi antenna | | |

| ENVIRONMENT AND MECHANICAL | |
|----------------------------|-------------------------------------------------|
| Temperature Range | 0 to 50° C - Operating, -20 to 60 ° C - Storage |
| Humidity (non-condensing) | 90% or less – Operating, 90% or less - Storage |

| PACKAGE CONTENT |
|--------------------------|
| ▶ EAP350 |
| ▶ Power Adapter (12V/1A) |
| ▶ CD with User's Manual |
| ▶ QIG |
| ▶ Ethernet cable |